







Model Number

NBB4-12GM50-E0-V1

Features

- Basic series
- 4 mm flush
- · Increased operating distance

Accessories

BF 12

Mounting flange, 12 mm

EXG-12

Quick mounting bracket with dead stop

V1-G

Female connector, M12, 4-pin, field attachable

V1-W

Female connector, M12, 4-pin, field attachable V1-G-2M-PUR

Female cordset, M12, 4-pin, PUR cable

V1-W-2M-PUR
Female cordset, M12, 4-pin, PUR cable

Technical Data General specifications

Nominal ratings

Switching element function		NPN	NO
Rated operating distance	s _n	4 mm	
Installation		flush	
Output polarity		DC	
Assured operating distance	sa	0 3.24 mn	า
Reduction factor r _{Al}		0.39	
Reduction factor r _{Cu}		0.35	
Reduction factor r ₃₀₄		0.75	
Reduction factor rarge		0.49	

10 ... 30 V 0 ... 800 Hz Operating voltage UB Switching frequency Hysteresis Н typ. 5% Reverse polarity protection reverse polarity protected Short-circuit protection pulsing U_{d} . ≤3 V Voltage drop Operating current 0 ... 200 mA

Off-state current I_r 0 ... 0.5 mA typ. 0.1 μ A at 25 °C No-load supply current I_0 \leq 15 mA Switching state indicator Multihole-LED, yellow

Switching state indicator

Functional safety related parameters

 MTTF_d
 1679 a

 Mission Time (T_M)
 20 a

 Diagnostic Coverage (DC)
 0 %

 Ambient conditions

Ambient temperature

Mechanical specifications

Connection type Connector M12 x 1 , 4-pin
Housing material brass, nickel-plated
Sensing face PBT
Degree of protection IP67

General information

Scope of delivery 2 self locking nuts in scope of delivery

Compliance with standards and directives

Standard conformity

Standards EN 60947-5-2:2007 IEC 60947-5-2:2007


Approvals and certificates

UL approval cULus Listed, General Purpose CSA approval cCSAus Listed, General Purpose


CCC approval CCC approval / marking not required for products rated ≤36 V

-25 ... 70 °C (-13 ... 158 °F)

Dimensions



Electrical Connection



Pinout



Wire colors in accordance with EN 60947-5-2

1	BN	(brown)
2	WH	(white)
3	BU	(blue)
4	BK	(black)